

Connect your M/S2150 to your Computer

Your M/S2150 must be connected to your computers serial port in order for it to communicate with your computer when you run the M/S2150 software. Please follow the steps below to connect your M/S2150 to your computer.

- 1 - Connect the RS 232 **"Input"** jack on the back of the M/S2150 to your computers serial port using the supplied cables and adapters. Your computer must have a standard RS 232 serial port with a DB 9 connector.



NOTE: If you have any other Tact digital amplifiers please disconnect their RS232 connection at this time.

- 2 - Turn on your M/S2150.

- 3 - Turn on your computer and start the M/S2150 System Software.



NOTE: You may receive a communication error message. Please close the message window and proceed to the next step.

- 4 - Select the **"Com"** button on the main software screen to open the communication window.

- 5 - Under the Operating Mode select **"Connect"**.

- 6 - Under the COM Port section select **"COM1"**. If you receive an **"invalid port number"** message please try selecting each of the port selections until you do not receive this message. If you receive this message on all COM ports you may not have a COM port installed on your computer. Please refer to your computer manufactures documentation for help to install a COM port.

- 7 - To verify that M/S2150 is properly connected to the host computer click on the **"Start"** button to perform the communication test. If everything is functioning properly you should see the results below. Press the **"Stop"** button after about 15 seconds to stop the test.

Rx Buf should display **"0"**.

Count should have counted in increments of 100.

Err Count should be **"0"**.

If the results are as above select the **"Close"** button to close the communication window. Your M/S2150 is now connected to your computer.

If the results are not as above please go back to step number **6** and select another COM port. Then repeat step 7.



NOTE: If you are still are not passing the communication test you may not have a COM port installed on your computer or you may have another device such as a modem or hand held PC that may be sharing the COM port on your computer. If you have a other Tact equipment attached it may be set to the same address. The M/S2150 requires a valid COM port that is not being used by any other devices.



NOTE: You will only have to select the communication port once. The next time you run the M/S2150 correction software it will remember your settings.